



## AW3834-T0-F

**Common Name** 16 Port, (4Px2/4Px2), Back to Back 65°, Low Band & Mid Band Small Cell Dual Sector

698-960MHz	8	Fixed	8.2	65°
1695-2690MHz	8	Fixed	14.2	65°
Frequency	Ports	Tilt	Gain	Beamwidth

## PRODUCT INFORMATION

This antenna solution is designed to offer Low Band and Mid Band functionality in a compact 2 foot high housing. This design is intended to offer 4 ports on Low Band and 4 ports on Mid Band for each antenna sector.

## APPLICATION

Alpha Wireless Low and Mid Band small cell Dual-sectors provide 65 degree coverage whilst in an ultra compact radome design. The antenna is designed to be installed in an urban environment where low visual impact is required. There are a number of mounting options available making deployments on lamp posts, utility poles, walls and other vertical structures possible.

## STANDARD & CERTIFICATIONS

Certification	BS EN ISO 9001:2015
---------------	---------------------



## FEATURES




- Multi-band Small Cell Dual-sector antenna - 698-960 / 1695-2690MHz.
- Compact design for low visual impact.
- Manufactured in Ireland.

*The parameters in this specification follow the definitions and recommendations per NGMN P-Basta, Release 9.6.*

## TECHNICAL SPECIFICATION

Electrical Specifications		Low Band				Mid Band			
Frequency Range per Input	MHz	698-755	755-820	820-890	890-960	1695-1995	1920-2170	2170-2500	2500-2690
Polarisation		+/- 45° Slant Linear							
Gain Basta	dBi	6.7±0.5	7.1±0.5	7.4±0.5	7.7±0.5	12.3±0.5	12.8±0.5	13.3±0.5	13.7±0.5
Gain Max	dBi	7.2	7.6	7.9	8.2	12.8	13.3	13.8	14.2
Azimuth Beamwidth	Degree	75°	72°	70°	66°	68°	66°	62°	58°
Azimuth Beam Squint	Degree <	5°	5°	5°	5°	5°	5°	5°	5°
Elevation Beamwidth	Degree	88° +/- 9°	72° +/- 8°	66° +/- 7°	64° +/- 8°	19° +/- 2°	17° +/- 2°	15° +/- 2°	13° +/- 2°
Electrical Downtilt	Degree	T0°	T0°	T0°	T0°	T0°	T0°	T0°	T0°
Electrical Downtilt Deviation	Degree <	5°	5°	5°	5°	1.5°	1.5°	1.5°	1.5°
Impedance	Ohms	50	50	50	50	50	50	50	50
VSWR	NA <	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5
Return Loss	dB >	14	14	14	14	14	14	14	14
Isolation	dB >	20	20	20	20	20	20	20	20
Passive Intermodulation	dBc <	-150	-150	-150	-150	-150	-150	-150	-150
Cross Polar Discrimination	dB >	16	16	16	16	16	16	16	16
Maximum Effective Power Per Port	W	100	100	100	100	250	250	250	250

### Representative Pattern Files



Low Band

Mid Band

Azimuth


Elevation

## TECHNICAL SPECIFICATION

### Mechanical Specifications

Dimensions	mm (in)	610 (24) x 365 (14.3) - (LxD)
Packing Size (LxWxD)	mm (in)	685 (27) x 448 (17.6) x 448 (17.6)
Net Weight (antenna)	kg (lb)	7.7 (17)
Net Weight (mount)	kg (lb)	5.9 (13)
Shipping Weight	kg (lb)	15.6 (34.4)
Connector Type (Female)	-	4.3-10
Connector Position	-	Bottom
Connector Quantity	-	16 ( 8P Low Band , 8P Mid Band)
Windload Frontal (at Rated Wind Speed: 150km/h)	N (lbf)	180 (40)
Windload Lateral (at Rated Wind Speed: 150km/h)	N (lbf)	180 (40)
Survival Wind Speed	km/h (mph)	200 (125)
Radome Material	-	ASA capped ABS
Radome Colour	RAL	7035 (light grey)
Product Compliance Environmental	-	RoHS
Lightning Protection	-	DC Grounded
Cold Temperature Survival	Celsius (Fahrenheit)	-40 (-40)
Hot Temperature Survival	Celsius (Fahrenheit)	70 (158)

### Array Layout and RET Information






Array	Frequency MHz	Ports
R1	617-894	1 - 2
R2	617-894	3 - 4
Y1	1695-2690	5 - 6
Y2	1695-2690	7 - 8

*Note: Coloured box sizes do not represent antenna sizes.*

TECHNICAL SPECIFICATION


Mechanical Illustration



## TECHNICAL SPECIFICATION

### Mounting Bracket Kit

CL-V-169 (Mounting Kit Included with Antenna)



Mounting Kit Tilt Range	Mounting Kit Material	Mounting Kit Pole Diameter
0	Stainless Steel	152mm-254mm (6" to 10")

### Ordering Info

#### Order Code - Antenna

AW3834-T0-F

#### Description

Zero degrees Fixed Tilt with 4.3-10 Connectors.

#### Order Code - Accessories

AW1012-2-FM-FM

#### Order Code - Accessories

RF Jumper Cable, connector types 4.3-10 (m) / 4.3-10 (m), length 2 metres (6'6")

AW1012-2-FM-NM

RF Jumper Cable, connector types 4.3-10 (m) / N-Type (m), length 2 metres (6'6")

AW1014-2-FM-TM

RF Jumper Cable, connector types 4.3-10 (m) / Nex10 (m), length 2 metres (6'6")

## Enquiries

#### Global Headquarters

Ashgrove Business Centre,  
Ballybrittas, Portlaoise, Ireland  
R32 DT0A, IRELAND  
[sales@alphawireless.com](mailto:sales@alphawireless.com)  
+353 57 86 33847

#### North America

7301 W. 129th Street, Suite 150,  
Overland Park,  
KS 66213, USA  
[sales@alphawireless.com](mailto:sales@alphawireless.com)  
+1 913 279 0008

#### Australia

3/76 Regentville Rd,  
Jamisontown,  
NSW 2750, AUSTRALIA  
[sales@alphawireless.com](mailto:sales@alphawireless.com)  
+ 61 2 4504 8212

## DISCLAIMER

The information in this document is provided solely regarding Alpha Wireless products. The information is not a guarantee of performance or characteristics. Alpha Wireless reserves the right to modify, change, amend, improve or make corrections to this document and its products, at any time and its sole discretion without prior written consent or notice. No license to any intellectual property rights is granted or implied under this document. Alpha Wireless disclaims warranties and liabilities of any kind including non-infringement of intellectual property rights of any third party.

© Alpha Wireless Limited 2022